PORTRONICS

VoltClock Charger

Wireless Charger With Alarm Clock



User Manual

I. Function Overview

II. Operation manual

1. Power Connection

1.1 Connect to Power:

- Plug the USB-A end of the cable into the power adapter. (Note- Minimum 18W Adaptor required for Optimum Output)
- Plug the Type-C end into the product.

1.2 Power Status:

- The product is ready and on standby when all indicators are lit.

2. Wireless Charging and USB-A Output

2.1 Wireless Charging:

- Output: 15W (Max)
- Indicator Display:
  - Power connection successful: flashes twice
  - Standby: light off
  - Charging: light on
  - Charged: light off
  - FOD (Foreign Object Detection): light flashes continuously

2.2 USB-A Output:

- Output: 5V/1A (Max)

3. Alarm Clock Functions

3.1 Button Functions:

- Light, M, SNOOZE, +, -

3.2 Time System Setting:

- Double-click the M button to switch between 12-hour and 24-hour formats. PM will display in the 12-hour format.

3.3 Time Setting:

- Click the M button once to set the hour, adjust with +/- (long press for continuous adjustment).
- Click the M button again to set the minutes, adjust with +/- (long press for continuous adjustment).
- Click the M button again to finish the time setting.

3.4 Alarm and Brightness Settings:

- Long press "+" to activate/deactivate Alarm 1, long press "-" to activate/deactivate Alarm 2. The alarm indicator lights up when activated.
- To set the alarm time, long press the M button to set the hour, adjust with +/- (long press for continuous adjustment), then click M to set the minutes, adjust with +/- (long press for continuous adjustment), and click M again to finish.
- The alarm rings for 3 minutes before auto shut-off without any operation.
- Press SNOOZE to enter Sleep Mode when the alarm rings; the alarm will ring again after 5 minutes. The indicator flashes during Sleep Mode. Short press "+" or "-" to stop Alarm 1 or Alarm 2 for the day, but it will ring the next day.
- Adjust display brightness in 5 levels by pressing "+" or "-". The default is the maximum brightness. Press "-" last to turn off the clock display light.

3.5 Perpetual Calendar & Temperature:

- Short press SNOOZE to check Year+Month+Day, auto exits after 5 seconds.
- Long press SNOOZE to set the calendar (YEAR→MONTH→DAY), adjust with +/- (long press for continuous adjustment).
- Double press SNOOZE to toggle between Celsius and Fahrenheit.

3.6 Night Light Setting:

- The night light has 8 color modes: RGB shade, red, yellow, light green, green, light blue, blue, pink.
- Press the Light button once to turn on with RGB shade; short press to switch colors, last press turns off the light.
- In RGB shade mode, short press Light to select a color; press again to switch to other colors.
- Long press Light to turn off the night light; turning it on again will recall the last used color.

3.7 Eco-power Function:

- Button cell is for timekeeping only.
- All functions stop during power disconnection and restore when power is reconnected.

4. Notice

- Use a QC3.0 or above power adapter for alarm, wireless charging, and USB output to work simultaneously.
- Avoid squeezing or colliding the product.
- Do not disassemble or expose to fire, water, to avoid short-circuit leakage.
- Avoid using in high temperatures, humidity, or corrosive environments.
- Keep away from magnetic cards to avoid malfunction.
- Maintain a 20cm distance from implanted medical devices to avoid interference.
- Keep out of children's reach.
- Keep the device away from water and liquids.
- Disconnect power before cleaning.
- Usage temperature: 0-45℃.
- Usage humidity: 20-85% (40℃).
- Warning: This product contains button batteries, which can cause serious injury if swallowed. Seek immediate medical attention if ingested.

Package Contents: Alarm charger, charging cable, User Manual (Power adapter not included. Please use a phone original adapter or purchase separately).

III. Specifications

- **Input:** DC 5V/3A; 9V/3A
- **Output:** 15W (MAX)
- **Charging Efficiency:** 73%
- **Charging Distance:** ≤6mm
- **USB-A Output:** 5V/1A (MAX)
- **Work Frequency:** 110-205KHz

PORTRONICS

www.portronics.com

For Support

Visit : www.portronics.com

E-mail : help@portronics.com

Contact No.: +91 9555245245

(**Working Hrs.:** Monday - Saturday 10:00am - 6:00pm)

E-Waste Management
E: info@3rrecycler.com

For E-Waste & ROHS compliance
refer to www.portronics.com/ewaste