


PORTRONICS

DASH 7 Ai

Wireless Microphone with Type-C Receiver



User Manual

Key Features

- **Easy to Use:** Just plug it in and start—no setup hassle.
- **Clearer Sound:** AI + Standard Noise Reduction cut out background noise.
- **No Delay:** Ultra-fast response with under 25ms latency.
- **All-Around Pickup:** Records sound clearly from every direction.
- **Crisp & Clear Audio:** Enjoy high-quality, lossless sound.
- **Record Together:** Capture audio from both mics at the same time.
- **Travel-Friendly:** Lightweight and compact to carry anywhere.

Package Contents

Microphone Transmitters: 1N
Type-C Receiver: 1N
Type-C Charging Cable: 1N
User Manual: 1N


Microphone specification

Frequency : 2.4 GHz	Frequency Range :20~20KHZ
Input Voltage : Dc 4.8~5.0V	Transmission Latency : 25 ms
Working Time : Up to 6 Hours	Indicator Light : Red/Green/Blue
Batter Capacity:70mAh(button cell)	Charging : Type C Port
Type : Digital Mic	Weight :6.7gm
Sensitivity ~26dBFS	Size:58.7x22.8x25 mm
S/N Ratio : 70 dB(A)	

Type-C Receiver specification

Frequency : 2.4 GHz
Indicator Light : Green
Input Voltage : Dc 4.8~5.0V
Charging : Plug In Device
Size : 44.34 x26.42 xx 9.52 mm

Product Illustration



1. Windproof net	5. Power Button
2. Microphone indicator	6. Receiver indicator
3. Microphone Type-C charging port	7. Type C port to connect phone
4. Microphone clip	8. Type C port of receiver

Transmitter (Microphone) Functions

- **Power On/Off:** Press and hold the power button for 3 seconds.
- **Noise Reduction (Single Click):**
 - **Green Light:** Noise Cancellation Off (Default)
 - **Yellow Light:** AI-Enhanced Noise Cancellation
 - **Blue Light:** Standard Noise Cancellation
- **Mute/Unmute (Double Click):**
 - **Red Light On:** Mic Muted
 - **Red Light Off:** Mic Active
- **Pairing Mode:** Red and blue lights flash ⇄ searching. Solid green ⇄ successfully connected.
- **Battery & Charging:**
 - **Flashing Red:** Low Battery
 - **Solid Red:** Charging
 - **Light Off:** Fully Charged
- **Type-C Port:** For charging the microphone.

Receiver Functions

- **Power On:** Just plug the receiver into your phone —it turns on automatically.
- **Flashing Green Light:** Searching for connection
- **Solid Green Light:** Successfully connected
- **Type-C Port:** Lets you charge your phone while the receiver is connected (power delivery supported).

Connection Instruction

1. **Turn On Microphone:** Press and hold the power button for 3 seconds. (Red and blue lights will start flashing.)
2. **Plug In Receiver:** Insert the USB-C receiver into your phone. It will power on automatically, and the green light will flash (pairing mode).
3. **Auto Pairing:** The microphone and receiver will connect automatically. When both show a solid green light, you're ready to record.
4. **Auto Power Off:** If not connected within 3 minutes, the microphone will turn off automatically.

Tip: For the best sound, keep the microphone within 20 cm of your mouth (for example, clipped to your collar).


PORTRONICS

www.portronics.com

For Support

Visit : www.portronics.com

Email : help@portronics.com

Contact No. : +91 9555245245, 011-42413131

(Working Hrs. : Monday – Saturday 10:00am – 6:00pm)



E-Waste Management
E:info@3recycler.com

For E-Waste & ROHS compliance
refer to www.portronics.com/ewaste

说明书（风琴折）105g双铜正反4C印刷 尺寸：65*75mm