



HARMONICS Y5

Wireless Stereo Headset

User Manual

SPECIFICATIONS

Charging

- Charging Port: Type-C
- Input: 5V – 0.2A
- Full Charge Time: approx. 2 hours

Earphone Audio

- Sensitivity: 98 ± 3 dB
- Rated Power: 3 mW
- Max Power: 5 mW
- Impedance: 16 Ω
- Frequency Response: 20 Hz – 20 kHz

Microphone

- Sensitivity: -42 ± 2 dB
- Frequency Response: 20 Hz – 20 kHz

Bluetooth

- Range: >10 m (line of sight)
- Version: Bluetooth V6.0
- Supported Profiles: HFP, HSP, A2DP, AVRCP

HOW TO USE

Charging

- Connect the Type-C cable to charge.
- Red light stays ON while charging.
- Takes about 2 hours to fully charge.
- Ice-blue light stays ON when fully charged.

Power & Pairing

- Power ON + Enter Pairing
- Long-press the Function Key for 2 seconds.
- LEDs flash red and ice-blue alternately.
- Voice prompt plays.

Power OFF

- Long-press the Function Key for 4 seconds.
- Red LED blinks with a voice prompt

Connection Status

- Connected: Voice prompt plays.
- Disconnected: LEDs flash red/ice-blue, voice prompt plays.

Call Controls

- Answer Call: Short-press Function Key
- Hang Up: Short-press Function Key
- Reject Call: Long-press Function Key for 2s
- Redial Last Number: Double-press Function Key

Music Controls

- Play/Pause: Short-press Function Key
- Next Track: Long-press Volume +
- Previous Track: Long-press Volume -
- Volume Up: Short-press Volume + (Beep at max)
- Volume Down: Short-press Volume -

Game/Music Mode

- Triple-Press Function Key.

Voice Assistant

- Press and hold Function Key for 2s, then release.

Multipoint Pairing (Two Phones)

1. Connect to Phone 1.
2. Turn off Bluetooth on Phone 1.
3. Connect to Phone 2.
4. Turn Bluetooth back on for Phone 1 and reconnect.

Clear Pairing / Reset

- In pairing mode, press Function Key 4 times.
- Earphone will power off and reset.

Notes

- If not paired within 5 minutes, earphone turns off.
- "Low Battery" voice prompt indicates charging needed.
- Battery level shown on Apple & most Android phones.



www.portronics.com

For Support

Visit : www.portronics.com

Email : help@portronics.com

Contact No. : +91 9555245245

(Working Hrs. : Monday - Saturday 10:00am - 6:00pm)



E-Waste Management
E: info@3rrecycler.com

For E-Waste & ROHS compliance
refer to www.portronics.com/ewaste