PORTRONICS

# LUXCELL MAGCLICK 10K

10000mAh Power Bank




Thank-you for choosing Portronics. We're happy to help you understand how to use this product. Read on!

SAFETY INSTRUCTIONS

## INTRODUCTION

Thank You For Purchasing Luxcell Magclick 10K Power Bank by Portronics! This 10,000mAh device charges your smartphones and USB devices on the go with a sleek design and digital battery display. This manual covers its features and usage. Thanks for choosing Portronics!

## PACKAGE CONTAINS

- Powerbank
- Charging Cable
- User Manual

## PRODUCT OVERVIEW




1. LED Digital Display
2. USB Output
3. Type-C Input/Output
4. Wake up Button
5. Magnetic Wireless Charging Area

## TECHNICAL SPECIFICATIONS

Capacity : 10000mAh
Input (Type-C) : DC 5V⎓3A/ 9V⎓2A
Output (Type-C) : DC 5V⎓3A/ 9V⎓2.22A/ 12V⎓1.67A(20W MAX.)
Output (USB) : DC 5V⎓3A/ 9V⎓2A/ 12V⎓1.5A/ 10V⎓2.25A(22.5W MAX.)
Magsafe Output : 5W/7.5W/10W/15W
Max Output(Type-C + USB-A) : DC 5V⎓3A

## GETTING STARTED

### 1. CHARGING YOUR POWERBANK

To charge your power bank, connect the Type-C port located on the power bank to a USB-A port or USB charger using the provided charging cable. Once charging begins, the LED display will show the charging percentage in real-time.

### 2. USING THE POWER BUTTON

- A button is located on the side of the Mobile Power Bank.
- Press the button once to turn on the power bank and view the remaining battery capacity on the LED display.
- To turn off the LED display, double-press the power button.

### 3. CHARGING YOUR MOBILE PHONE

To charge your mobile phone using the power bank, simply connect your device using USB-A and Type -C Port with the provided charging cable.

## SAFETY INSTRUCTIONS

### 1. STORAGE

- Store in a Safe Environment: Keep the power bank in a cool, dry place. Avoid direct sunlight, excessive heat (such as inside a parked car), or freezing temperatures.
- Partial Charge for Long-Term Storage: If not used for a long period, store the power bank at 50–60% charge.
- Avoid Moisture: Keep away from water or humid conditions to prevent short circuits or corrosion.

### 2. HANDLING & USAGE SAFETY

- Inspect Regularly: Stop using the power bank if you notice swelling, cracks, or exposed wires.
- Avoid Physical Impact: Do not drop, crush, or apply pressure.
- Keep Away from Metal Objects: Avoid contact with coins, keys, or metal items.
- Prevent Overheating: If it becomes unusually hot, unplug and allow it to cool.
- Do Not Disassemble: Never open or repair the power bank yourself.
- Do Not Keep in Pockets During Use: Avoid keeping the power bank in your pocket while it is operating. Always hold it in your hand or place it on a flat, open surface.

### 3. CHARGING INSTRUCTIONS

- Use Correct Cable & Charger: Use the provided or certified high-quality accessories only.
- Avoid Overcharging: Unplug once fully charged.
- Do Not Overcharge Overnight: Avoid leaving the power bank plugged in overnight.
- Do Not Charge & Discharge Simultaneously.
- Charge in a Safe Area: Place on a flat, non-flammable surface.

### 4. UNSAFE USAGE CONDITIONS

- Do not place on beds, cushions, or under pillows.
- Do not store in pockets or bags with metal objects.
- Keep away from heaters or radiators.
- Do not leave on car dashboards under sunlight.

### 5. LOAD & PERFORMANCE SAFETY

Do Not Overload: Connect only devices within the rated output capacity.

### 6. AIR TRAVEL SAFETY

- Carry power banks only in hand baggage.
- Do not charge devices using the power bank during flights.

### 7. FIRE SAFETY

- In Case of Fire: Use a Class D fire extinguisher or sand.
- Do Not Use Water.

### 8. DISPOSAL & RECYCLING

Dispose responsibly at authorized electronic waste recycling centers.

## HANDLING A SWOLLEN POWER BANK

If your power bank swells, stop using it immediately and unplug it carefully, placing it on a non-flammable surface away from flammable items, people, and pets to avoid risks like leaks or explosions. Do not puncture or open it; instead, let it cool down and dispose of it at an electronics recycling center per local rules—never in regular trash. Contact the manufacturer for further advice

## IMPORTANT NOTE

The company will not be responsible for any damage, injury, or malfunction resulting from improper usage, mishandling, or failure to follow the manufacturer's instructions

PORTRONICS

E-Waste Management
E: info@3rrecycler.com

For E-Waste & ROHS compliance
refer to www.portronics.com/ewaste

**www.portronics.com**

**For Support**
**Visit :** www.portronics.com
**Email :** help@portronics.com
**Contact No. :** +91 9555245245
**(Working Hours. :** Monday - Saturday 10:00am - 6:00pm)